

| SCHEDULE OF SPECIFICATIONS AND QUANTITIES FOR ELECTRICAL WORKS OF <u>ATM</u> AT PROPOSED PURULIA MUNSIFDANGA BRANCH FOR UCO BANK | | | | | |
|--|---|-----|------|-----------|--------------|
| SL. NO | DESCRIPTION | QTY | UNIT | RATE(Rs.) | AMOUNT (Rs.) |
| 1 | Wiring with 2nos. 10 sqmm + 2nos. 2.5 sqmm Cu wire laid through PVC pipe from UPS Rm to ATM room.including supply of wires and necessary accessories | 15 | Mtr | | |
| 2 | Supply & installation of 4WAY TPN DB comprising of the following- 4way TPN DB- 1no., 63A MCB- 2no., 20A SP MCB- 2nos. ETC. | 2 | Set | | |
| 3 | Supply & laying 25mm diameter PVC conduit for LAN wiring for ATM. | 15 | Mtr | | |
| 4 | Supply, laying connection of CAT-6 wire through PVC rigid pipe from HUB of ATM room. | 10 | Mtr | | |
| 5 | Supply & fixing of I/O box with cover complete RJ-45 connector. | 1 | Nos | | |
| 6 | Supply & drawing of 3 x 1.5 sqmm wire through PVC pipe for ATM Gate supply. | 8 | Mtr | | |
| 7 | Supply & installation of Timer box for Glow sign supply comprising of the following- 1 no. SP MCB, 1no. 25A Contactor, 1no. 24 Hours Timer. | 1 | Set | | |
| 8 | Supply & installation of ATM power outlet points comprising of the following- 15A socket- 2nos., 16A switch with indicator- 2nos., 6m box & plate- 1set. | 2 | Set | | |
| 9 | Supply & installation of SPN DB comprising of the following- 8way DB- 1no., 32A DP MCB- 1no., 16/20A SP MCB- 4nos. | 2 | Set | | |
| 10 | Supply & installation of AC starter having starter 11-18A, 16A socket & 3pin plug top. | 2 | Set | | |
| 11 | 32A DP MCB with MCB Box for UPS input & output. | 2 | Set | | |
| 12 | S/F of 2 x 6 + 1x2.5 sqmm CU wire through PVC pipe for UPS & AC line. | 14 | Mtr | | |
| 13 | Light point wiring with 3x1.5 sqmm wire through PVC pipe. | 7 | Nos | | |
| 14 | S/F of Recessed Light fixtures with 1nos. 15W LED PANEL lighter. | 7 | Nos | | |
| 15 | S/F of Tube light fittings with 1x28 w T5 lamps. | 1 | No | | |
| 16 | S/F of 2x2.5 + 1x1.5 sqmm Cu wire through PVC pipe for Glow Sign board supply. | 12 | Mtr | | |
| 17 | Earth pit with 3mtr. Long and 2" dia. G.I. pipe upto 8' ht to 10' ht. | 2 | No | | |
| 18 | Supply & installation of UPS outlet points comprising of the following- 6A socket- 2nos., 6A switch with indicator- 2nos., 6m box & plate- 1 set. | 2 | Set | | |
| 19 | Supply & installation of Raw power outlet points comprising of the following- 16A socket- 2nos., 16A switch with indicator- 2nos., 3m box & plate- 1set. | 2 | Set | | |
| 20 | Supply & fixing of 10 sqmm Cu wire for connection of earthing to main switch. | 12 | Mtr | | |
| | TOTAL | | | | |
| | Rupees + GST | | | | |